

INSTALLATION INSTRUCTIONS BAMBOO PENDANT WITH P1BX HANGING SYSTEM

These instructions cover the BAMBOO luminaire with the following options:

| SERIES | HANGING SYSTEM | SIZE | LIGHT SOURCE | CONTROL | WIRE DIAGRAM |
|-----------------|--|------|--------------|---|------------------------|
| 1. BA1 - BAMBOO | P1BX: PENDANT WITH EMERGENCY DRIVER IN SURFACE MOUNT CANOPY, SINGLE CENTER AIRCRAFT CABLE AND POWER CORD | 04" | STATIC WHITE | DM1: 0-10V DIM 1% DM3: LUTRON HILUME ECOSYSTEM 1% (LDE1) | WIRE DIAGRAM ON PAGE 5 |




FIG. 1 - BA1-P1BX-04-MW-XXX-LEDX_XXK-UNV-XX-DM~

GENERAL NOTES:

1. PLEASE COMPLETELY READ THE INSTALL INSTRUCTIONS BEFORE STARTING INSTALLATION.
2. TURN OFF POWER TO CIRCUIT FIXTURE WHILE IT IS BEING INSTALLED.
3. INSTALL IN ACCORDANCE WITH ALL LOCAL, STATE AND NATIONAL CODES CONSULT WITH A QUALIFIED ELECTRICIAN FOR PROPER INSTALLATION.
4. CAREFULLY UNPACK ALL CONTENTS; SOME COMPONENTS MAY HAVE BEEN SHIPPED IN SEPARATE BOXES MOST FIXTURES ARE SHIPPED PARTIALLY ASSEMBLED. SOME UNASSEMBLY MAY BE REQUIRED FOR INSTALLATION.
5. FIXTURE POWER CORD WIRES ARE LOW- VOLTAGE. DO NOT CONNECT TO LINE VOLTAGE OR DAMAGE TO THE FIXTURE WILL OCCUR AND WARRANTY WILL BE VOIDED.
6. DO NOT LET THE BAMBOO LUMINAIRE HANG FREE UNTIL THE CABLE IS SECURED AND EVENLY TENSIONED.
7. DUE TO A CHANGE IN NEC SECTION 410.69 EFFECTIVE IN 2022, THE COLOR PINK WILL BE USED IN PLACE OF GRAY FOR 0-10V CONTROL. NOTE THAT EXISTING SYSTEMS AND FIXTURES MANUFACTURED PRIOR TO 2022 MAY STILL USE GRAY WIRE AS AN UNGROUNDED CONDUCTOR FOR 0-10V CONTROL. CARE SHOULD BE TAKEN WHEN WORKING ON EXISTING SYSTEMS.

OCL Architectural Lighting

Phone: 314.863.1895
Fax: 314.863.3278
www.ocl.com

Table of Contents

GENERAL INFORMATION: 3

MOUNTING:..... 4

BAMBOO MOUNTING [CANOPY]: 4

BA1-P1BX-INSTALLATION-INSTRUCTIONS

GENERAL INFORMATION:

You will receive the following with each BAMBOO series pendant fixture:

1. BAMBOO LUMINAIRE with CORD attached. (Pre-assembled as shown in FIG. 2)
2. INSTALLATION INSTRUCTIONS (shown in FIG. 3) - Please completely read the install instructions before starting installation.
3. RED BAG (shown in FIG. 3) contains below following items.
 - a. CANOPY SUBASSEMBLY (as shown in FIG. 4)
 - b. WALL PLATE (as shown in FIG. 5)
 - c. STRAIN RELIEF (as shown in FIG. 6)

WARNING: Examine all components for any damage before beginning installation.

WARNING: This fixture should be installed by a licensed electrician only.

WARNING: Be careful not to scratch or damage any finished parts.




FIG.2 BAMBOO LUMINAIRE
(PRE-ASSEMBLED)




FIG.3 RED BAG AND
INSTALLATION INSTRUCTIONS




FIG. 4 - CANOPY SUBASSEMBLY




FIG. 5 - WALL PLATE




FIG. 6 - STRAIN RELIEF

BA1-P1BX-INSTALLATION-INSTRUCTIONS

MOUNTING: BAMBOO MOUNTING [CANOPY]:

1. Turn off power to circuit fixture while it is being installed.
2. Unscrew the CANOPY FINIAL and remove CANOPIES. Be careful not to scratch finish as shown in FIG. 7.
3. Attach MOUNTING PLATE to JUNCTION BOX (by other) as shown below in FIG. 8.




FIG. 7 – CANOPY DIS-ASSEMBLY




FIG. 8 – MOUNTING PLATE ASSEMBLY INSTALLATION




FIG. 9 – MOUNTING PLATE ASSEMBLED VIEW

4. Raise the BAMBOO FIXTURE and pass the cord through CANOPY FINIAL, CANOPY AND ALL THREAD. ADJUST FIXTURE DROP TO DESIRED HEIGHT as shown below in FIG. 10. Mark cord with marker inside of DRIVER MOUNTING BRACKET as shown below in FIG. 11. Trim off excess cord leaving minimum of 8.00" past the top of the DRIVER MOUNTING BRACKET all thread as shown below in FIG. 12.




FIG. 10 – FIXTURE INSTALLATION




FIG. 11 -CORD INSTALLATION




FIG.12 – DETAIL SHOWING CORD TRIM INFORMATION

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.ocl.com

BA1-P1BX-INSTALLATION-INSTRUCTIONS

- Insert cord through the strain relief and tighten two screws on the strain relief above hanging bracket where marked. If screws are not properly tightened cord could slip through the strain relief, causing the fixture to fall as shown in FIG. 13.


WARNING:



Do not let the BAMBOO LUMINAIRE hang free until CABLE is secured and evenly tensioned.

- Make wire connections between Building Supply, Driver and fixture cord inside the junction box (by others) in accordance with the NATIONAL ELECTRICAL CODE and all applicable LOCAL AND STATE CODES. See WIRE LABEL TABLE and WIRE DIAGRAM shown in FIG. 14 and FIG. 15 for wire connections.

TIGHTEN SCREWS ALL THE WAY



CORD


FIG. 13 – STRAIN RELIEF WITH CORD INSERTED

| WIRE DIAGRAM TABLE | | | | | | |
|--------------------|----------------|-----------|------------------|----------------------|---|------------------------|
| SERIES | HANGING SYSTEM | BODY SIZE | BODYLIGHT SOURCE | LED OUTPUT | CONTROL | WIRE DIAGRAM |
| BA1 BAMBOO | P1BX | 04" | STATIC WHITE | LED1 LED2 LED3 | DM1: 0-10V DIM 1% DM3: LUTRON HILUME ECOSYSTEM 1% (LDE1) | WIRE DIAGRAM ON PAGE 5 |

| WIRE LABEL TABLE | | |
|------------------|---------------|------------------|
| CONTROL | WIRE COLOR | LABEL |
| ALL | RED(CORD) | LED(+) |
| ALL | BLUE(CORD) | LED(-) |
| ALL | GREEN(CORD) | GROUND |
| ALL | BLACK | LINE VOLTAGE |
| ALL | WHITE | NEUTRAL |
| ALL | GREEN(DRIVER) | GROUND |
| ALL | RED/WHITE | LED(+) |
| ALL | BLUE/WHITE | LED(-) |
| ALL | RED/BLACK | TEST(+) |
| ALL | RED/WHITE | TEST(-) |
| ALL | BLACK/ORANGE | UNSWITCHED POWER |
| DM1 | PURPLE | 0-10V(+) |
| DM1 | PINK | 0-10V(-) |
| DM3 | PURPLE | E2 |
| DM3 | PINK | E1 |

FIG. 14 – WIRE LABEL INFORMATION

NOTE: Below captured WIRE DIAGRAM for Reference only. Please refer to the installation instructions from the manufacturer of the LED EMERGENCY DRIVER for complete wiring diagram/specifications.



SEE GENERAL NOTE 7 ON PAGE 1

FIG. 15 – WIRE DIAGRAM

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.ocl.com

BA1-P1BX-INSTALLATION-INSTRUCTIONS

7. Swing DRIVER MOUNTING BRACKET back over and secure it with KNURLED NUT removed in step 2.
8. Raise CANOPY and secure to ceiling by threading the FINIAL as shown below in FIG. 16 to the NIPPLE (available in MOUNTING BRACKET ASSEMBLY).




FIG. 16 – FINIAL INSTALLATION

9. Restore power to circuit the BAMBOO series pendant is connected to.
 - a. Test to see that the luminaire turns on after power is restored.
 - b. Contact OCL for any luminaire troubleshooting if a problem occurs.




FIG. 17 - COMPLETED INSTALLATION OF BAMBOO PENDANT WITH P1BX HANGING SYSTEM

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.ocl.com