


INSTALLATION INSTRUCTIONS REV PENDANT WITH P1EU HANGING SYSTEM

These instructions cover the REV luminaire with the following options:

SERIES	HANGING SYSTEM	SIZE	LIGHT SOURCE	CONTROL	WIRE DIAGRAM
1. RV1(INNER ILLUMINATION) 2. RV2(OUTER ILLUMINATION)	P1EU: PENDANT WITH 4 ANGLED AIRCRAFT CABLES AND POWER CORD TO CANOPY; MOUNTS TO 4X4 OCTAGON J-BOX (BY OTHERS) REMOTE DRIVER ENCLOSURE	24	STATIC WHITE	0-10V DIM 1% (DM1)	WIRE DIAGRAM A ON PAGE 5
		36	STATIC WHITE	0-10V DIM 1% (DM1)	WIRE DIAGRAM A ON PAGE 5
		48	STATIC WHITE	0-10V DIM 1% (DM1)	WIRE DIAGRAM B ON PAGE 6
		60	STATIC WHITE	0-10V DIM 1% (DM1)	WIRE DIAGRAM B ON PAGE 6
		72	STATIC WHITE	0-10V DIM 1% (DM1)	WIRE DIAGRAM B ON PAGE 6



GENERAL NOTES:

- PLEASE COMPLETELY READ THE INSTALL INSTRUCTIONS BEFORE STARTING INSTALLATION.
- INSTALL IN ACCORDANCE WITH ALL LOCAL, STATE AND NATIONAL CODES CONSULT WITH A QUALIFIED ELECTRICIAN FOR PROPER INSTALLATION.
- CAREFULLY UNPACK ALL CONTENTS; SOME COMPONENTS MAY HAVE BEEN SHIPPED IN SEPARATE BOXES. MOST FIXTURES ARE SHIPPED PARTIALLY ASSEMBLED. SOME UNASSEMBLY MAY BE REQUIRED FOR INSTALLATION.
- REMOTE MOUNTING DRIVERS - OCL RECOMMENDS: MAX 30' (WIRE LENGTH) DISTANCE FROM FIXTURE FOR NON-DIMMING AND DM1. MAX 10' (WIRE LENGTH) REMOTE DISTANCE FOR LUTRON. ENCLOSURE SHOULD REMAIN ACCESSIBLE AFTER INSTALLATION.
- FIXTURE POWER CORD WIRES ARE LOW-VOLTAGE. DO NOT CONNECT TO LINE VOLTAGE OR DAMAGE TO THE FIXTURE WILL OCCUR AND WARRANTY WILL BE VOIDED.
- DO NOT LET THE REV LUMINAIRE HANG FREE UNTIL BOTH THE AIRCRAFT CABLES ARE SECURED AND EVENLY TENSIONED.
- KEEP HANDS AWAY FROM THE SILICONE DIFFUSER. DO NOT TOUCH IT AT ALL TIMES.

OCL Architectural Lighting

Phone: 314.863.1895
Fax: 314.863.3278
www.ocl.com

Table of Contents

GENERAL INFORMATION.....	3
REMOTE DRIVER MOUNTING	4
WIRE DIAGRAM A (FOR 24" & 36").....	5
WIRE DIAGRAM B (FOR 48",60" & 72")	6
MOUNTING.....	7
REV MOUNTING [CANOPY]	7
CORD INSTALLATION INSTRUCTIONS	9

RV1_RV2-P1EU-XX-STATICWHITE-INSTALL-INSTRUCTIONS

GENERAL INFORMATION:

You will receive the following with each REV P1EU series pendant fixture:

1. REV LUMINAIRE. (Pre-assembled as shown in FIG. 3)
2. INSTALLATION INSTRUCTIONS - Please completely read the install instructions before starting installation.
3. HARDWARE BAG
 - a. CANOPY (Grounding wires Pre-assembled as shown in FIG. 4)
 - b. MOUNTING KIT (as shown in FIG. 5)
 - i. FINIAL
 - ii. MOUNTING BRACKET ASSEMBLY
4. REMOTE DRIVER BOX WITH DRIVER INSTALLED (as shown in FIG. 6)

WARNING: Examine all components for any damage before beginning installation.

WARNING: This fixture should be installed by a licensed electrician only.

WARNING: Be careful not to scratch or damage any finished parts.




FIG. 3 - REV LUMINAIRE




FIG. 4 - CANOPY




FIG. 5 - MOUNTING KIT CONTENTS




FIG. 6 - REMOTE DRIVER BOX
WITH DRIVER INSTALLED

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.oclighting.com

RV1_RV2-P1EU-XX-STATICWHITE-INSTALL-INSTRUCTIONS

REMOTE DRIVER MOUNTING:

1. Shut off power.
2. Remove the lid of the REMOTE DRIVER HOUSING as shown in FIG. 7 and FIG. 8 below.




FIG. 7 – REMOTE DRIVER BOX
ASSEMBLY FOR 24 & 36 MODELS




FIG. 8 – REMOTE DRIVER BOX
ASSEMBLY FOR 48, 60 & 72 MODELS

3. Mount the REMOTE DRIVER HOUSING to code in a location that is 30 feet or less from the FIXTURE BODY and is accessible after installing. Max wire length is 30ft measured from the FIXTURE BODY to the DRIVER.
4. Using the knockout holes at the bottom of the remote box, run conduit into the remote box for the building supply wires (line voltage) and conduit out of the remote box for the fixture wire (low voltage). Conduit, adapters and wires are supplied by other.

NOTE: Do not run Line Voltage and Low Voltage wires in the same conduit.

5. Depending upon the size of the fixture (see WIRE DIAGRAM TABLE on Page 5 for correct Wire Diagram) run (1) set of positive and negative 16 or larger gauge wire (by others) or (2) set of positive and negative 16 or larger gauge wire (by others) from the REMOTE DRIVER HOUSING to the junction box the fixture will mount to (by others). Inside the REMOTE DRIVER HOUSING, connect:
 - Driver 1 LED output (+) and positive 16 or larger gauge wire (1st set).
 - Driver 1 LED output (-) and negative 16 or larger gauge wire (1st set).
 - Driver 2 (if applicable) LED output (+) and positive 16 or larger gauge wire (2nd set).
 - Driver 2 (if applicable) LED output (-) and negative 16 or larger gauge wire (2nd set).
 - Dimming wires as shown on the driver in FIG. 9 and FIG. 10 below.




FIG. 9 – WIRE CONNECTION FROM
BUILDING SUPPLY TO J-BOX FOR 24 & 36
MODELS




FIG. 10 – WIRE CONNECTION FROM
BUILDING SUPPLY TO J-BOX FOR 48, 60
& 72 MODELS

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.oclighting.com

RV1_RV2-P1EU-XX-STATICWHITE-INSTALL-INSTRUCTIONS

6. Connect building supply wires to the driver. See WIRE DIAGRAM TABLE below for correct WIRE DIAGRAM. Refer to correct diagram for wire connections. Make all wire connections in accordance with the national electrical code and all applicable local and state codes. Install the lid on the remote driver housing once connections are done.

WIRE DIAGRAM TABLE						
SERIES	HANGING SYSTEM	BODY SIZE	LIGHT SOURCE	LED OUTPUT	CONTROL	WIRE DIAGRAM
1. RV1 (INNER ILLUMINATION)	P1EU	24	STATIC WHITE	LED1&LED2	0-10V DIM 1% (DM1)	WIRE DIAGRAM A ON PAGE 5
	P1EU	36	STATIC WHITE	LED1&LED2	0-10V DIM 1% (DM1)	WIRE DIAGRAM A ON PAGE 5
	P1EU	48	STATIC WHITE	LED1&LED2	0-10V DIM 1% (DM1)	WIRE DIAGRAM B ON PAGE 6
2. RV2 (OUTER ILLUMINATION)	P1EU	60	STATIC WHITE	LED1&LED2	0-10V DIM 1% (DM1)	WIRE DIAGRAM B ON PAGE 6
	P1EU	72	STATIC WHITE	LED1&LED2	0-10V DIM 1% (DM1)	WIRE DIAGRAM B ON PAGE 6

WIRE DIAGRAM A (FOR 24" & 36"):

DRIVER WIRES TO BUILDING SUPPLY

BLACK WIRE = LINE VOLTAGE
WHITE WIRE = NEUTRAL
GREEN WIRE = GROUND
PURPLE = DIM +
GREY = DIM -

FIG. 11 – WIRE CONNECTION FROM BUILDING SUPPLY TO DRIVER

WIRE LABEL TABLE

CONTROL	WIRE	LABEL
ALL	INSULATED WIRE	LED +
ALL	BRAIDED WIRE	LED -

FIG. 12 – WIRE CONNECTION FROM DRIVER TO FIXTURE CORD




FIG. 13 – WIRE DIAGRAM FOR 24" & 36" MODELS

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.ocllighting.com

RV1_RV2-P1EU-XX-STATICWHITE-INSTALL-INSTRUCTIONS

WIRE DIAGRAM B (FOR 48",60" & 72"):

DRIVER WIRES TO BUILDING SUPPLY

BLACK WIRE = LINE VOLTAGE
WHITE WIRE = NEUTRAL
GREEN WIRE = GROUND
PURPLE = DIM +
GREY = DIM -

FIG. 14 – WIRE CONNECTION FROM BUILDING SUPPLY TO DRIVER

WIRE LABEL TABLE

CONTROL	WIRE COLOR	LABEL
ALL	WHITE	DRIVER 1 LED +
ALL	BLACK	DRIVER 1 LED -
ALL	PURPLE	DRIVER 2 LED +
ALL	GREY	DRIVER 2 LED -

FIG. 15 – WIRE CONNECTION FROM DRIVER TO FIXTURE CORD




FIG. 16 – WIRE DIAGRAM FOR 48",60" & 72" MODELS

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.ocl.com

RV1_RV2-P1EU-XX-STATICWHITE-INSTALL-INSTRUCTIONS

MOUNTING:
REV MOUNTING [CANOPY]:

7. Assemble the MOUNTING BRACKET ASSEMBLY to the JUNCTION BOX the fixture will mount to (by others) with screws (by others) as shown in FIG. 17 below.
8. Pass the CANOPY through the AIRCRAFT CABLE and CORD in such a way that the AIRCRAFT CABLE goes through the oblong slot hole and CORD passes through the center hole on the CANOPY as shown in FIG. 18 below.




FIG. 17 – MOUNTING BRACKET ASSEMBLY INSTALLATION




FIG. 18 – CANOPY PLATE INSTALLATION

9. Raise the REV LUMINAIRE up, with multiple people, to the ceiling and feed the AIRCRAFT CABLE through the GRIPLOCK and CORD through NIPPLE which is available in MOUNTING BRACKET ASSEMBLY. Adjust the AIRCRAFT CABLE to the desired length as shown in FIG. 19 & 20 below.

NOTE: Make sure to trim the excess of AIRCRAFT CABLE, leaving at least 1.75" past the GRIPLOCK for the GRIPLOCK to function properly. Make sure that the aircraft cable is taped up above the GRIPLOCK, so there is no chance of any shortage.




FIG. 19 - INSTALLATION VIEW




FIG. 20 – CANOPY DETAIL VIEW

WARNING:


1. Do not let the REV LUMINAIRE hang free until the AIRCRAFT CABLES are secured and evenly tensioned.
2. Keep hands away from the SILICONE DIFFUSER. Do NOT touch it at all times.

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.oclighting.com

10. Make all wire connections in the inside the junction box (by others) in accordance with the national electrical code and all applicable local and state codes. See wire diagram on page 5 and 6 and instruction on how to shorten/install the cord on page 9.

11. Raise CANOPY and secure to ceiling by threading the FINIAL to the NIPPLE (MOUNTING BRACKET ASSEMBLY) until fully seated as shown in FIG. 21.




FIG. 21 - FINIAL INSTALLATION

12. Restore power to circuit the REV series pendant is connected to.
 - a. Test to see that the luminaire turns on after power is restored.
 - b. Contact OCL for any luminaire troubleshooting if a problem occurs.




FIG. 22 - COMPLETED INSTALLATION OF REV PENDANT WITH P1EU HANGING SYSTEM RV1 (INNER ILLUMINATION) (SHOWN)




FIG. 23 - COMPLETED INSTALLATION OF REV PENDANT WITH P1EU HANGING SYSTEM RV2 (OUTER ILLUMINATION) (SHOWN)

13. If there is option for Acoustic Panel, place the Acoustic part above the fixture body such that it is eventually balanced and assembly concentrically to the axis of fixture body as shown in FIG. 24 and 25 below for both RV1 and RV2 Series.




FIG. 24 - RV1 (INNER ILLUMINATION) (WITH ACOUSTIC PANEL SHOWN)




FIG. 25 - RV2 (OUTER ILLUMINATION) (WITH ACOUSTIC PANEL SHOWN)

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.oclighting.com

CORD INSTALLATION INSTRUCTIONS

- Strip off 1.00" of outer clear insulation exposing the outer metal braiding as shown in FIG. 26 below. **Be careful not to cut or damage the outer metal braiding.** Gently push braiding down to loosen the individual braids exposing the inner insulated wire as shown in FIG. 27 below.




FIG. 26




FIG. 27

- Using a small pointed object, begin unweaving the exposed metal braiding as shown in FIG. 28 below. Position the unwoven metal strands on one side of the inner insulated wire and twist the individual strands together as shown in FIG. 29 below.




FIG. 28




FIG. 29

- Using electrical tape, insulate the twisted strands leaving 0.188" exposed for connections. Strip off 0.188" of the inner insulation as you normally would for 18AWG stranded core wire as shown in FIG. 30 below. Connect the inner insulated wire (+) to the positive 16 gauge or larger wire ran in step 5 at the hanging bracket and Connect the outer braiding (-) to the negative 16 gauge or larger wire ran in step 5 at the hanging bracket FIG. 31 below.




FIG. 30




FIG. 31

OCL Architectural Lighting

Phone: 314.863.1895

Fax: 314.863.3278

www.oclighting.com